

Paquímetro - adição de fração de polegada - metrologia - vernierônio
 Prof. Eduardo J. Stefanelli - www.stefanelli.eng.br

Aluno: _____ N° _____ RA: _____

mesmo denominador $\text{a) } \frac{3''}{4} + \frac{3''}{128} = \frac{96''}{128} + \frac{3''}{128} =$	resultado $\frac{99''}{128}$	mesmo denominador $\text{aa) } 1. \frac{11''}{16} + \frac{1''}{128} = 1. \frac{88''}{128} + \frac{1''}{128} =$
$\text{b) } \frac{3''}{8} + \frac{1''}{32} =$	$\text{ab) } 4. \frac{5''}{8} + \frac{5''}{128} =$	resultado $1. \frac{89''}{128}$
$\text{c) } \frac{1''}{8} + \frac{1''}{64} =$	$\text{ac) } \frac{3''}{8} + \frac{3''}{64} =$	
$\text{d) } \frac{11''}{16} + \frac{1''}{32} =$	$\text{ad) } \frac{11''}{16} + \frac{3''}{64} =$	
$\text{e) } \frac{1''}{4} + \frac{5''}{128} =$	$\text{ae) } 4. \frac{5''}{16} + \frac{3''}{128} =$	
$\text{f) } \frac{5''}{8} + \frac{3''}{64} =$	$\text{af) } 1. \frac{1''}{8} + \frac{3''}{64} =$	
$\text{g) } \frac{3''}{8} + \frac{1''}{128} =$	$\text{ag) } \frac{7''}{8} + \frac{1''}{128} =$	
$\text{h) } \frac{5''}{8} + \frac{3''}{128} =$	$\text{ah) } 2. \frac{5''}{8} + \frac{1''}{32} =$	
$\text{i) } \frac{15''}{16} + \frac{1''}{128} =$	$\text{ai) } 4. \frac{1''}{4} + \frac{1''}{128} =$	
$\text{j) } \frac{7''}{16} + \frac{5''}{128} =$	$\text{aj) } 2. \frac{7''}{8} + \frac{1''}{128} =$	
$\text{k) } \frac{1''}{8} + \frac{1''}{32} =$	$\text{ak) } \frac{13''}{16} + \frac{1''}{32} =$	
$\text{l) } \frac{13''}{16} + \frac{3''}{128} =$	$\text{al) } 4. \frac{1''}{4} + \frac{3''}{64} =$	
$\text{m) } \frac{7''}{8} + \frac{1''}{32} =$	$\text{am) } \frac{7''}{16} + \frac{5''}{128} =$	
$\text{n) } \frac{3''}{16} + \frac{3''}{128} =$	$\text{an) } 2. \frac{15''}{16} + \frac{5''}{128} =$	

$$\text{o) } \frac{1''}{2} + \frac{1''}{128} =$$

$$\text{p) } \frac{1''}{16} + \frac{1''}{32} =$$

$$\text{q) } \frac{15''}{16} + \frac{3''}{128} =$$

$$\text{r) } \frac{5''}{8} + \frac{1''}{32} =$$

$$\text{s) } \frac{15''}{16} + \frac{5''}{128} =$$

$$\text{t) } \frac{1''}{4} + \frac{3''}{128} =$$

$$\text{u) } \frac{1''}{4} + \frac{3''}{128} =$$

$$\text{v) } \frac{1''}{8} + \frac{3''}{128} =$$

$$\text{w) } \frac{5''}{8} + \frac{3''}{64} =$$

$$\text{x) } \frac{1''}{16} + \frac{1''}{32} =$$

$$\text{y) } \frac{11''}{16} + \frac{1''}{64} =$$

$$\text{z) } \frac{7''}{8} + \frac{3''}{64} =$$

$$\text{ao) } 4 \cdot \frac{1''}{2} + \frac{1''}{32} =$$

$$\text{ap) } \frac{1''}{4} + \frac{1''}{32} =$$

$$\text{aq) } 2 \cdot \frac{9''}{16} + \frac{3''}{64} =$$

$$\text{ar) } 2 \cdot \frac{1''}{16} + \frac{1''}{128} =$$

$$\text{as) } \frac{13''}{16} + \frac{3''}{64} =$$

$$\text{at) } 2 \cdot \frac{3''}{16} + \frac{1''}{32} =$$

$$\text{au) } 4 \cdot \frac{7''}{8} + \frac{3''}{64} =$$

$$\text{av) } 3 \cdot \frac{9''}{16} + \frac{1''}{128} =$$

$$\text{aw) } \frac{3''}{8} + \frac{3''}{64} =$$

$$\text{ax) } 4 \cdot \frac{1''}{2} + \frac{1''}{128} =$$

$$\text{ay) } 1 \cdot \frac{5''}{8} + \frac{3''}{64} =$$

$$\text{az) } 3 \cdot \frac{1''}{2} + \frac{3''}{64} =$$